

Disposable Digital Forehead Thermometer Products

Instructions for Use

How to Read

- 1. Remove backing liner and apply monitor to center of forehead, just above the eyebrows. Skin surface should be clean and dry.
- 2. Read thermometer when the boxes stop changing color (generally 15 seconds), and while it is still on the forehead. For most accurate measurement, have a friend or colleague read the thermometer.
- 3. Green indicates the correct temperature. If green does not appear, temperature is between blue and tan.

Intended Use

• Measure human forehead surface temperature and monitor temperature trends

Accuracy

±1°F (0.6°C)

Storage & Handling

• ^{15.6°C} Store at 60 to 104°F (15.6 to 40°C)

• Optimal storage at 60 to 80°F (15.6°C to 26.7°C) in 40 to 60% RH

Precautions

- Environmental temperatures might affect the performance of this product
- Product should be used indoors at normal room temperature



- Avoid exposure to UV light
- If cleaning is required, use soap and water or rubbing alcohol



This adhesive backed Liquid Crystal Forehead Temperature Trend Monitor is designed to be a single use device. Should the device be reused, the adhesive properties may not be sufficient for product to adhere properly to the skin which could affect the measuring performance of the device.

Liquid Crystal Forehead Temperature Trend Monitors are designed to be unbreakable noninvasive, quick reading devices that reliably indicate trends in core body temperature by measuring the surface temperature of the forehead. Liquid Crystal Forehead Temperature Trend Monitors indirectly measure core body temperature by measuring the forehead temperature, whereas clinical thermometers (oral/rectal) directly measure core body temperature. Unusual Liquid Crystal Forehead Temperature Trend Monitor readings should be verified by a clinical thermometer.

For external use only • Conforms to ASTM E-1061-01 • Not made with natural rubber latex

www.tiptemp.com

TIP TEMPerature Products - 340 W Broad Street, Burlington, NJ 081016 - 1-800-TIP-TEMP